

QNF-868W Transmitter specifications

LCD screen	53x25mm
Tone frequency	130kHz
The Max. distance of tracing cable	2000 m
Max. distance of cable mapping	2000m
Max. distance of cable length testing	1000 m
Trace cable connected to switch	Anti-jamming
Tone mode	2 Tones, adjustable
Compatible with connectors	RJ11,RJ45,BNC,USB
LED lights display	Wiremap, tone, tracing
Cable map indication	LCD (#1- #8)
Shielded indication	LCD (#9)
Low battery display	LCD (6.5V)
Battery type	DC9.0V (NEDA 1604/6F22 DC9V) x1pc
Dimension(LxWxD)	185 x 80 x 32mm

QNF-868W Receiver specifications

Frequency	130kHz
The Max. working current	Less than 70mA
Earphone jack	1
LED illumination	2 LEDs
Battery type	DC9.0V (NEDA 1604/6F22 DC9V) x1pc
Dimensions (LxWxD)	218 x 46 x 29mm

QNF-868W Remote unit specifications

Remote identifier	8 pcs
Compatible with connectors	RJ11, RJ45, BNC
Dimension(LxWxD)	106x32x30mm